INTEL(R) E7500 High Performance Appliance Platform -Intel(R) XEON(TM) Processor or Low Voltage Intel (R) XEON(TM) Processor with 512 KB L2 Cache

IO BOARD SCHEMATIC

PAGE	DESCRIPTION
1	CONTENT
2	REVISION CHANGES
3	BLOCK DIAGRAM
4	LAYOUT NOTICE
5	LAYOUT NOTICE
6	TABLES
7	P64H2#1 PCI-X BUS A,B
8	P64H2#1 HUB,POWER,GND
9	P64H2#1 TERMINATORS
10	P64H2#2 PCI-X BUS A,B
11	P64H2#2 HUB, POWER,GND
12	P64H2#2 TERMINATORS
13	P64H2#3 PCI-X BUS A,B
14	P64H2#3 HUB,POWER,GND
15	P64H2#3 TERMINATORS
16	GIGABIT/COPPER BUS INTERFACE
17	GIGABIT/COPPER POWER/GND/RJ45
18	GIGABIT FIBER1 PCI-X BUS INTERFACE
19	GIGABIT FIBER1 POWER/GND/SERDES
20	GIGABIT FIBER2 PCI-X BUS INTERFACE
21	GIGABIT FIBER 2 POWER/GND/SERDES
22	PCI-X SLOT
23	MICTOR HUB INTERFACE

IO BOARD SCHEMATIC rev 1.01

Intel Corporation		
Title: IO BOARD		
Size	Document Number: CONTENT	Rev: 1.01
Date: Monday, August 26, 2002	Sheet 1 of 23	

IO BOARD SCHEMATIC rev 0.91 non NDA
IO BOARD SCHEMATIC rev 1.01 non NDA supporting Intel(R) Xeon(TM) and Low Voltage Intel XEON(TM) processors with 512 KB L2 Cache

Intel Corporation		
Title	IO BOARD	
Size	Document Number: REVISION CHANGES	Rev: 1.01
Date: Monday, August 26, 2002	Sheet 2 of 23	

INTEL(R) E7500 High Performance Appliance Platform Intel(R) XEON(TM) Processor or Low Voltage Intel (R) XEON(TM) Processor with 512 KB L2 Cache



Intel Corporation		
Title: IO BOARD		
Size	Document Number: BLOCK DIAGRAM	Rev: 1.01
Date: Monday, August 26, 2002	Sheet 3 of 23	

Intel Corporation	
Title	IO BOARD
Size	Document Number: LAYOUT NOTICE — Rev: 1.01
Date: Monday, August 26, 2002	Sheet 4 of 23

Intel Corporation

Title

IO BOARD

Size	Document Number	Rev
	LAYOUT NOTICE	1.01

Date: Monday, August 26, 2002 Sheet 5 of 23

CONNECTORS:

J1: ITP PORT
J2: COPPER GIGABIT PORT
J3: FIBER GIGABIT PORT
J4: FIBER GIGABIT PORT
J5: PCI-X SLOT
J6: USB PORT
J7: USB PORT
J8: RESET BUTTON
J9: COM1 PORT
J10: POWER BUTTON
J11: PS/2 KB/MOUSE
J12: 10/100M BITS RJ45
J13: 10/100M BITS RJ45
J14: 10/100M BITS RJ45
J15: LEDS CONNECTOR
IDE1: PRIMARY IDE CONNECTOR
IDE2: SECONDARY IDE CONNECTOR
ATX1: ATX POWER CONNECTOR
CPUFAN1: CPU FAN POWER CONNECTOR
CPUFAN2: CPU FAN POWER CONNECTOR

JUMPERS:

JP1: DP/UP SELECTION FOR ITP PORT
1-2 DP DEFAULT
2-3 UP
JP2: CPU SAFE MODE
ON ENABLE DEFAULT
OFF DISABLE
JP3: CLEAR CMOS
1-2 NORMAL DEFAULT
2-3 CLEAR CMOS
JP4: ICH3 TCO TIMER
ON DISABLE
OFF ENABLE DEFAULT
JP5: VRM ID SELECTION
JP6: CPU FAN POWER
1-2 +12V
2-3 5V

INTERRUPT ROUTING TABLES:

ICH3 INTERRUPT:
PIRQA#: P64H2#1
PIRQB#: P64H2#2
PIRQC#: P64H2#3
PIRQD#: NO USE
PIRQE#: 82559#1
PIRQF#: 82559#2
PIRQG#: 82559#3
PIRQH#: NO USE

P64H2#1
P1AIRQ0: 82544GC#1 FOR COPPER
P1BIRQ0: 82544GC#2 FOR FIBER

P64H2#2
P2AIRQ0: 82544GC#1 FOR FIBER

P64H2#3:
P3AIRQ0: PCI-X SLOT
P3AIRQ1: PCI-X SLOT
P3AIRQ2: PCI-X SLOT
P3AIRQ3: PCI-X SLOT

GPIO FOR LEDS

GPIO34: LED CONTROL FOR POWER LED
GPIO35: LED CONTROL FOR CPU OVER HEAT LED
GPIO36: LED CONTROL FOR PRIMARY HDD LED
GPIO37: LED CONTROL FOR SECONDARY HDD LED
GPIO38: LED CONTROL FOR 10/100M BIT PORT1 ACTIVITY LED
GPIO39: LED CONTROL FOR 10/100M BIT PORT2 ACTIVITY LED
GPIO40: LED CONTROL FOR 10/100M BIT PORT3 ACTIVITY LED
GPIO41: LED CONTROL FOR GIGABIT PORT1 ACTIVITY LED
GPIO42: LED CONTROL FOR GIGABIT PORT2 ACTIVITY LED
GPIO43: LED CONTROL FOR GIGABIT PORT3 ACTIVITY LED

Intel Corporation			
Title: IO BOARD			
Size	Document Number: LAYOUT NOTICE 2		Rev: 1.01
Date: Monday, August 26, 2002	Sheet 6 of 23		









Intel Corporation		
Title: IO BOARD		
Size	Document Number: P64H2#1 PCI-X BUS A, B	Rev: 1.01
Date: Monday, August 26, 2002	Sheet 7 of 23	



Intel Corporation		
Title	IO BOARD	
Size	Document Number: P64H2#1 HUB, POWER, GND	Rev: 1.01
Date: Monday, August 26, 2002	Sheet 8 of 23	









































Intel Corporation

Title: IO BOARD

Size | Document Number: P64H2#1 TERMINATORS | Rev: 1.01

Date: Monday, August 26, 2002 | Sheet 9 of 23









Intel Corporation		
Title: IO BOARD		
Size	Document Number: P64H2#2 PCI-X BUS A, B	Rev: 1.01
Date: Monday, August 26, 2002	Sheet 10 of 23	



Intel Corporation		
Title	IO BOARD	
Size	Document Number P64H2#2 HUB, POWER, GND	Rev 1.01
Date: Monday, August 26, 2002	Sheet 11 of 23	































Intel Corporation

Title: IO BOARD

Size | Document Number: P64H2#2 TERMINATORS | Rev: 1.01

Date: Monday, August 26, 2002 | Sheet 12 of 23









Intel Corporation

Title: IO BOARD

Size | Document Number: P64H2#3 PCI-X BUS A, B | Rev: 1.01

Date: Monday, August 26, 2002 | Sheet 13 of 23



Intel Corporation		
Title	IO BOARD	
Size	Document Number: P64H2#3 HUB, POWER, GND	Rev: 1.01
Date: Monday, August 26, 2002	Sheet 14 of 23	



Intel Corporation		
Title: IO BOARD		
Size	Document Number: P64H2#3 TERMINATORS	Rev: 1.01
Date: Monday, August 26, 2002	Sheet 15 of 23	













Title	Intel Corporation IO BOARD	
Size	Document Number GIGABIT/COPPER BUS INTERFACE	Rev 1.01
Date: Monday, August 26, 2002	Sheet 16 of 23	


U5D
82544GC
U5C
82544GC
VCC3
VCC2_5
VCC1_8
VCC1_5
VCC1_8
VCC3
U6
H5007_TRANSFORMER
J1
RJ45
LED1
GIGA_LED
Intel Corporation
IO BOARD
GIGABIT/COPPER POWER/GND/RJ45
Monday, August 26, 2002
Sheet 17 of 23
Rev 1.01


U8A
P1B_AD0 P1B_AD1 P1B_AD2 P1B_AD3 P1B_AD4 P1B_AD5 P1B_AD6 P1B_AD7 P1B_AD8 P1B_AD9 P1B_AD10 P1B_AD11 P1B_AD12 P1B_AD13 P1B_AD14 P1B_AD15 P1B_AD16 P1B_AD17 P1B_AD18 P1B_AD19 P1B_AD20 P1B_AD21 P1B_AD22 P1B_AD23 P1B_AD24 P1B_AD25 P1B_AD26 P1B_AD27 P1B_AD28 P1B_AD29 P1B_AD30 P1B_AD31 P1B_AD32 P1B_AD33 P1B_AD34 P1B_AD35 P1B_AD36 P1B_AD37 P1B_AD38 P1B_AD39 P1B_AD40 P1B_AD41 P1B_AD42 P1B_AD43 P1B_AD44 P1B_AD45 P1B_AD46 P1B_AD47 P1B_AD48 P1B_AD49 P1B_AD50 P1B_AD51 P1B_AD52 P1B_AD53 P1B_AD54 P1B_AD55 P1B_AD56 P1B_AD57 P1B_AD58 P1B_AD59 P1B_AD60 P1B_AD61 P1B_AD62 P1B_AD63
AD0 AD1 AD2 AD3 AD4 AD5 AD6 AD7 AD8 AD9 AD10 AD11 AD12 AD13 AD14 AD15 AD16 AD17 AD18 AD19 AD20 AD21 AD22 AD23 AD24 AD25 AD26 AD27 AD28 AD29 AD30 AD31 AD32 AD33 AD34 AD35 AD36 AD37 AD38 AD39 AD40 AD41 AD42 AD43 AD44 AD45 AD46 AD47 AD48 AD49 AD50 AD51 AD52 AD53 AD54 AD55 AD56 AD57 AD58 AD59 AD60 AD61 AD62 AD63
CBE#0 CBE#1 CBE#2 CBE#3 CBE#4 CBE#5 CBE#6 CBE#7
P1B_CBE#0 P1B_CBE#1 P1B_CBE#2 P1B_CBE#3 P1B_CBE#4 P1B_CBE#5 P1B_CBE#6 P1B_CBE#7
PAR PAR64
P1B_PAR P1B_PAR64
FRAME# IRDY# TRDY# STOP# IDSEL DEVSEL#
P1B_FRAME# P1B_IRDY# P1B_TRDY# P1B_STOP# P1B_AD20 P1B_DEVSEL#
R110 100
REQ# GNT# REQ64# ACK64# LOCK#
P1B_REQ#0 P1B_GNT#0 P1B_REQ64# P1B_ACK64# P1B_PLOCK#
INTA#
P1B_IRQ0
CLK
P1B_PCLK0
M66EN
P1B_M66EN
RST#
P1B_PCIRST#
SERR# PERR#
P1B_SERR# P1B_PERR#
VIO1 VIO2
GLAN2_VIO GLAN2_VIO
ZN_COMP ZP_COMP
GLAN2_ZNCOMP GLAN2_ZPCOMP
LAN_PWR_GOOD PME# APM_WAKEUP AUX_PWR PWR_STATE0 PWR_STATE1
GIGA_PWROK
GLAN2_PME#
GLAN2_AUXPWR
82544GC
VCC3
U7
G2EECS G2EECLK G2EEDI G2EEDO
CS SK DI DO VCC NC NC GND
9346
C27 .1U
R107 1K
U8B
G2EEDI G2EEDO G2EECS G2EECLK
EE_DI EE_DO EE_CS EE_SK
FL_ADDR0 FL_ADDR1 FL_ADDR2 FL_ADDR3 FL_ADDR4 FL_ADDR5 FL_ADDR6 FL_ADDR7 FL_ADDR8 FL_ADDR9 FL_ADDR10 FL_ADDR11 FL_ADDR12 FL_ADDR13 FL_ADDR14 FL_ADDR15 FL_ADDR16 FL_ADDR17 FL_ADDR18
FL_CS# FL_OE# FL_WE#
FL_DATA0 FL_DATA1 FL_DATA2 FL_DATA3 FL_DATA4 FL_DATA5 FL_DATA6 FL_DATA7
XTAL1 XTAL2
25MHZ
C28 22P
C29 22P
JTAG_TCK JTAG_TDI JTAG_TDO JTAG_TMS JTAG_TRST
G2TCK G2TRST
GMII_TEST0 GMII_TEST1
COL_TEST CRS_TEST
R115 R116 R117 1K
LOS XOFF XON ABV_HI BLW_LO TBI_MODE
F1_LOSLINK
R108 R109 1K
SDP0 SDP1 SDP2 SDP3 SDP4 SDP6 SDP7
TP8 TP9 TP10 TP11 TP12 TP13 TP14 TEST POINT
R111 1K
TX_DATA0 TX_DATA1 TX_DATA2 TX_DATA3 TX_DATA4 TX_DATA5 TX_DATA6 TX_DATA7 TX_DATA8 TX_DATA9
F1_TXD0 F1_TXD1 F1_TXD2 F1_TXD3 F1_TXD4 F1_TXD5 F1_TXD6 F1_TXD7 F1_TXD8 F1_TXD9
GTX_CLK EWRAP TEST0 TEST1
R112 22 F1_REFCLK
F1_EWRAP
R113 680
GLAN2_TEST1
RX_DATA0 RX_DATA1 RX_DATA2 RX_DATA3 RX_DATA4 RX_DATA5 RX_DATA6 RX_DATA7 RX_DATA8 RX_DATA9
F1_RXD0 F1_RXD1 F1_RXD2 F1_RXD3 F1_RXD4 F1_RXD5 F1_RXD6 F1_RXD7 F1_RXD8 F1_RXD9
RBC0 RBC1
F1_RBC0 F1_RBC1
REF
R114 2.49K-1
MDI-0 MDI+0 MDI-1 MDI+1 MDI-2 MDI+2 MDI-3 MDI+3
82544GC
VCC3
R118 10K GLAN2_TEST1
R119 10K GLAN2_PME#
R122 33.2-1 GLAN2_ZNCOMP
R123 53.6-1 GLAN2_ZPCOMP
R124 1K GLAN2_AUXPWR
P1B_M66EN
C31 .01U
VCC3
R120 100K
GLAN2_VIO
C30 .01U
VCC3
R121 1K G2TCK
R125 1K G2TRST
Intel Corporation
Title
IO BOARD
Size
Document Number
GIGABIT FIBER1 PCI-X BUS INTERFACE
Rev 1.01
Date: Monday, August 26, 2002
Sheet 18 of 23



Intel Corporation	
Title	IO BOARD
Size	Document Number: GIGABIT FIBER1 PWR/GND/SERDIUS — Rev: 1.01
Date: Monday, August 26, 2002	Sheet 19 of 23


U11A
P2A_AD0 P2A_AD1 P2A_AD2 P2A_AD3 P2A_AD4 P2A_AD5 P2A_AD6 P2A_AD7 P2A_AD8 P2A_AD9 P2A_AD10 P2A_AD11 P2A_AD12 P2A_AD13 P2A_AD14 P2A_AD15 P2A_AD16 P2A_AD17 P2A_AD18 P2A_AD19 P2A_AD20 P2A_AD21 P2A_AD22 P2A_AD23 P2A_AD24 P2A_AD25 P2A_AD26 P2A_AD27 P2A_AD28 P2A_AD29 P2A_AD30 P2A_AD31 P2A_AD32 P2A_AD33 P2A_AD34 P2A_AD35 P2A_AD36 P2A_AD37 P2A_AD38 P2A_AD39 P2A_AD40 P2A_AD41 P2A_AD42 P2A_AD43 P2A_AD44 P2A_AD45 P2A_AD46 P2A_AD47 P2A_AD48 P2A_AD49 P2A_AD50 P2A_AD51 P2A_AD52 P2A_AD53 P2A_AD54 P2A_AD55 P2A_AD56 P2A_AD57 P2A_AD58 P2A_AD59 P2A_AD60 P2A_AD61 P2A_AD62 P2A_AD63
AD0 AD1 AD2 AD3 AD4 AD5 AD6 AD7 AD8 AD9 AD10 AD11 AD12 AD13 AD14 AD15 AD16 AD17 AD18 AD19 AD20 AD21 AD22 AD23 AD24 AD25 AD26 AD27 AD28 AD29 AD30 AD31 AD32 AD33 AD34 AD35 AD36 AD37 AD38 AD39 AD40 AD41 AD42 AD43 AD44 AD45 AD46 AD47 AD48 AD49 AD50 AD51 AD52 AD53 AD54 AD55 AD56 AD57 AD58 AD59 AD60 AD61 AD62 AD63
CBE#0 CBE#1 CBE#2 CBE#3 CBE#4 CBE#5 CBE#6 CBE#7
P2A_CBE#0 P2A_CBE#1 P2A_CBE#2 P2A_CBE#3 P2A_CBE#4 P2A_CBE#5 P2A_CBE#6 P2A_CBE#7
PAR PAR64
P2A_PAR P2A_PAR64
FRAME# IRDY# TRDY# STOP# IDSEL DEVSEL#
P2A_FRAME# P2A_IRDY# P2A_TRDY# P2A_STOP# P2A_AD20 P2A_DEVSEL#
R134 100
REQ# GNT# REQ64# ACK64# LOCK#
P2A_REQ#0 P2A_GNT#0 P2A_REQ64# P2A_ACK64# P2A_PLOCK#
INTA# CLK M66EN RST# SERR# PERR#
P2A_IRQ0 P2A_PCLK0 P2A_M66EN P2A_PCIRST# P2A_SERR# P2A_PERR#
VIO1 VIO2
GLAN3_VIO GLAN3_VIO
ZN_COMP ZP_COMP
GLAN3_ZNCOMP GLAN3_ZPCOMP
LAN_PWR_GOOD PME# APM_WAKEUP AUX_PWR PWR_STATE0 PWR_STATE1
GIGA_PWROK GLAN3_PME# GLAN3_AUXPWR
82544GC
U10
G3EECS G3EECLK G3EEDI G3EEDO
CS SK DI DO VCC NC NC GND
9346
VCC3
C34 .1U
R131 1K
U11B
G3EEDI G3EEDO G3EECS G3EECLK
EE_DI EE_DO EE_CS EE_SK
FL_ADDR0 FL_ADDR1 FL_ADDR2 FL_ADDR3 FL_ADDR4 FL_ADDR5 FL_ADDR6 FL_ADDR7 FL_ADDR8 FL_ADDR9 FL_ADDR10 FL_ADDR11 FL_ADDR12 FL_ADDR13 FL_ADDR14 FL_ADDR15 FL_ADDR16 FL_ADDR17 FL_ADDR18
FL_CS# FL_OE# FL_WE#
FL_DATA0 FL_DATA1 FL_DATA2 FL_DATA3 FL_DATA4 FL_DATA5 FL_DATA6 FL_DATA7
XTAL1 XTAL2
JTAG_TCK JTAG_TDI JTAG_TDO JTAG_TMS JTAG_TRST
GMII_TEST0 GMII_TEST1
COL_TEST CRS_TEST
LOS XOFF XON ABV_HI BLW_LO
F2_LOSLINK
R132 R133 1K
SDP0 SDP1 SDP2 SDP3 SDP4 SDP6 SDP7
TP15 TP16 TP17 TP18 TP19 TP20 TP21 TEST POINT
TBI_MODE
R135 1K
TX_DATA0 TX_DATA1 TX_DATA2 TX_DATA3 TX_DATA4 TX_DATA5 TX_DATA6 TX_DATA7 TX_DATA8 TX_DATA9
F2_TXD0 F2_TXD1 F2_TXD2 F2_TXD3 F2_TXD4 F2_TXD5 F2_TXD6 F2_TXD7 F2_TXD8 F2_TXD9
GTX_CLK EWRAP TEST0 TEST1
R136 22 F2_REFCLK
F2_EWRAP
R137 680
GLAN3_TEST1
RX_DATA0 RX_DATA1 RX_DATA2 RX_DATA3 RX_DATA4 RX_DATA5 RX_DATA6 RX_DATA7 RX_DATA8 RX_DATA9
F2_RXD0 F2_RXD1 F2_RXD2 F2_RXD3 F2_RXD4 F2_RXD5 F2_RXD6 F2_RXD7 F2_RXD8 F2_RXD9
RBC0 RBC1
F2_RBC0 F2_RBC1
REF
R138 2.49K-1
MDI-0 MDI+0 MDI-1 MDI+1 MDI-2 MDI+2 MDI-3 MDI+3
82544GC
Y3 25MHZ
C35 22P
C36 22P
G3TCK
G3TRST
R139 R140 R141 1K
VCC3
R142 10K GLAN3_TEST1
R143 10K GLAN3_PME#
R146 33.2-1 GLAN3_ZNCOMP
R147 53.6-1 GLAN3_ZPCOMP
R148 1K GLAN3_AUXPWR
P2A_M66EN
C38 .01U
R144 100K
GLAN3_VIO
C37 .01U
R145 1K G3TCK
R149 1K G3TRST
Intel Corporation
Title
IO BOARD
Size
Document Number
GIGABIT FIBER2 PCI-X BUS INTERFACE
Rev 1.01
Date: Monday, August 26, 2002
Sheet 20 of 23


U11D
82544GC
U11C
82544GC
VCC3
VCC1_8
VCC2_5
VCC1_5
VCC3SD
BC176
BC177
BC178
BC179
BC180
BC181
BC182
BC183
BC184
BC185
BC186
BC187
BC188
BC189
BC190
BC191
BC193
BC194
BC195
BC196
BC198
BC199
BC200
BC201
BC202
BC203
BC204
BC205
BC206
BC207
BC208
BC209
BC210
BC211
BC212
BC213
BC214
BC215
BC216
BC217
BC218
BC300
10U-12/10V
1U-08
.1U
1000P
FB2
30_OHM-08/1A
L6
L7
L8
L9
1UH-1008
R150
10K
GLAN3ACT#
R151
100-1
R152
R153
150-1
R154
1K
U12
HDMP-1636A_0
C39
C40
F2_TXD0
F2_TXD1
F2_TXD2
F2_TXD3
F2_TXD4
F2_TXD5
F2_TXD6
F2_TXD7
F2_TXD8
F2_TXD9
F2_RXD0
F2_RXD1
F2_RXD2
F2_RXD3
F2_RXD4
F2_RXD5
F2_RXD6
F2_RXD7
F2_RXD8
F2_RXD9
F2_RBC0
F2_RBC1
F2_REFCLK
F2_EWRAP
F2_LOSLINK
ODINP
ODINN
ODOUTP
ODOUTN
J3
AGILENT_OP_CON_HFBR-53A5VEM
VEER
RD+
RD-
SD
VCCR
VCCT
TD-
TD+
VEET
LINK_UP#
RX_ACTIVITY#
TX_ACTIVITY#
LINK10#
LINK100#
LINK1000#
Intel Corporation
IO BOARD
GIGABIT FIBER2 PWR/GND/SERDIUS
Monday, August 26, 2002
Sheet 21 of 23
Rev 1.01



















Intel Corporation		
Title: IO BOARD		
Size	Document Number: PCI-X SLOT	Rev: 1.01
Date: Monday, August 26, 2002	Sheet 22 of 23	